



EW-7612UAn

## 300Mbps Wireless 802.11b/g/n USB Adapter



Simply plug your new Edimax EW-7612UAn USB adapter into your computer's USB port, and you can enjoy high-speed wireless network access in just a few seconds. This wireless USB adapter provides a quick and simple way to add or upgrade the wireless connectivity of your desktop, laptop, or notebook computer. You can enjoy transfer rates as high as 300Mbps\* when your Edimax EW-7612UAn USB adapter is connected to wireless 802.11n-compatible devices.

### Wireless 802.11n Standard (data rates up to 300Mbps\*)

Edimax EW-7612UAn has an extended wireless coverage and a higher data transfer rate. It is equipped with the latest wireless technology, which enables it to eliminate wireless dead spots while extending its wireless coverage by 4 times. The EW-7612UAn USB adapter is compatible with IEEE802.11b/g/n wireless standards, and is capable of transferring data at up to 300Mbps when connected to 802.11n wireless devices. The wireless technology in the Edimax EW-7612UAn USB adapter also extends its wireless signal distance, and provides more reliable wireless connections than traditional IEEE802.11b/g wireless networks.

### Features a Hardware WPS (Wi-Fi Protected Setup) Button

Wi-Fi Protected Setup (WPS) is a new technology designed to establish a secure wireless network in a fast and easy way. If the wireless device you wish to connect supports WPS, the Edimax EW-7612UAn USB adapter will be able to establish a secure, encrypted WPA data connection with it. All you need to do is press the button, and you are set to go. The Edimax EW-7612UAn USB adapter supports both hardware (button) and software (web page) WPS.

### Features Multi-Language EZmax Setup Wizard\*


Edimax EW-7612UAn includes an EZmax setup wizard—a setup application available in 16 languages, which will assist you in connecting your new EW-7612UAn USB adapter with wireless networks in no time.

### Built-in 3dBi Antenna and Hardwire USB Cable for Improved Wireless Performance

EW-7612UAn not only has a built-in 3dBi high gain antenna, it is also bundled with a free hardwire USB cable for improved wireless performance. When using EW-7612UAn with the hardwire USB cable, it provides better wireless performance at no extra cost.

\* Receive PHY rate : 300Mbps  
Transmit PHY rate : 150Mbps.

\* The EZMax Setup CD Wizard only supports the Edimax wireless Series.



## FEATURES AND TECHNICAL SPECIFICATIONS

- Complies with wireless 802.11b/g/n standards with data rate up to 300Mbps\*
- Extends wireless coverage for 4 times\*
- Includes multi-language EZmax setup wizard.
- Supports 64/128-bit WEP, WPA, WPA2, WPS and IEEE802.1x encryption for wireless security
- Supports WMM

HARDWARE INTERFACE	STANDARD	FREQUENCY BAND
<ul style="list-style-type: none"> <li>1 USB 1.0/2.0 Type A</li> <li>Hardware WPS button</li> <li>high gain 3 dBi Antennas</li> </ul>	<ul style="list-style-type: none"> <li>IEEE802.11b, 802.11g, 802.11n</li> </ul>	<ul style="list-style-type: none"> <li>2.4000~2.4835GHz (Industrial Scientific Medical Band)</li> </ul>
DATA RATE	INSTALLATION	LED
<ul style="list-style-type: none"> <li>11b: 1/2/5.5/11Mbps ; 11g: 6/9/12/24/36/48/54Mbps</li> <li>11n (20MHz): MCS0-7, 32 with half guard Interval support (up to 72Mbps)</li> <li>11n (40MHz): MCS0-7, 32 with half guard Interval support (up to 150Mbps)</li> </ul>	<ul style="list-style-type: none"> <li>Multi-language EZmax Setup Wizard</li> </ul>	<ul style="list-style-type: none"> <li>Link/Activity</li> </ul>
SECURITY	DIMENSION	HUMIDITY & TEMPERATURE
<ul style="list-style-type: none"> <li>WEP 64/128, WPA, WPA2 and IEEE802.1x</li> <li>Supports WMM</li> <li>Hardware and Software WPS configuration</li> </ul>	<ul style="list-style-type: none"> <li>155(H) x 15(W) x 15(D) mm</li> </ul>	<ul style="list-style-type: none"> <li>Max. 95% (Non Condensing)</li> <li>32~104°F (0~40°C)</li> </ul>
SYSTEM REQUIREMENTS	OUTPUT POWER	CERTIFICATIONS
<ul style="list-style-type: none"> <li>Windows 2000/XP/Vista/7, Mac 10.4.x or above and Linux</li> </ul>	<ul style="list-style-type: none"> <li>11n: 14dBm±1dBm,</li> <li>11g: 14dBm±1dBm,</li> <li>11b: 17dBm±1dBm</li> </ul>	<ul style="list-style-type: none"> <li>CE, FCC</li> </ul>

## NETWORK SETUP DIAGRAM AND RELATED PRODUCTS

Example Edimax EW-7612UAn setup:

- Plug the mini wireless adapter into your computer.
- Setup the wireless connection by running EZmax wizard.
- Connect to 802.11b/g/n wireless access point or wireless broadband router.



\* Receive PHY rate : 300Mbps  
Transmit PHY rate : 150Mbps.

\* Maximum performance may vary depending on network conditions and environmental factors.